

SIP gateway management

To create a new SIP gateway, you must send a POST request to the address of the **Webitel Engine** server with the specified request body. The following is an example of such a request:

POST /api/v2/gateway

Content-Type: application/json
X-Access-Token: eyJ0eXAiOiJKV1QiLCJhbGciOiJIUzI1NiJ9.eyJpZCI6ImNmMTQ3ZTFiLTk1ZGYtNDI1OC05ZTM2LWQ4NWZkZDZlZDUzZiIsImV4cCI6MTQ5NzkwNjAwMDAwMCwiZCI6InNpdGUiLCJ0IjoizG9tYWluIiwiaWwiOiI6Mn0.0-bcG_U3oJMN4r3YaBfSg9CcrZPANZulcapR4E6TSdg

BODY

```
{
  "name": "myGW",
  "username": "4952-200",
  "password": "dvxhH5Lm32",
  "realm": "pbx.zadarma.com",
  "profile": "external",
  "domain": "test06.webitel.com",
  "params": [
    {
      "name": "register",
      "value": "true"
    },
    {
      "name": "extension-in-contact",
      "value": "true"
    }
  ],
  "var": [],
  "ivar": [],
  "ovar": []
}
```

The structure of the request body is described in the table below:

#	Title	Type	Value
2	name	string	The unique name of the SIP gateway
3	username	string	SIP Username
4	password	string	SIP password
5	realm	string	SIP realm / domain
6	profile	string	SIP profile, one of the following values is specified: <ul style="list-style-type: none">nonreg - for SIP trunk without registration (5060/udp)external - to connect to the SIP provider by login and password (5080/udp)
7	domain	string	Webitel domain with which the gateway is associated.
8	params	array	An array of additional parameters for FreeSWITCH ..
9	var ivar ovar	array	Additional variables .

Information viewing, updating or deletion occurs through GET, PUT and DELETE requests, respectively:

GET /api/v2/gateway/myGW

X-Access-Token: eyJ0eXAiOiJKV1QiLCJhbGciOiJIUzI1NiJ9.eyJpZCI6ImNmMTQ3ZTFiLTk1ZGYtNDI1OC05ZTM2LWQ4NWZkZDZlZDUzZiIsImV4cCI6MTQ5NzkwNjAwMDAwMCwiZCI6InNpdGUiLCJ0IjoizG9tYWluIiwiaWwiOiI6Mn0.0-bcG_U3oJMN4r3YaBfSg9CcrZPANZulcapR4E6TSdg