

Configure Outbound Routing

In order for a user to call through the *Youmagic* gateway, open [Callflow - Default](#) in [Webitel WebClient](#). **Default** is the outgoing route, users and devices enter it after registering with the Webitel server. Let's create a simple ACR Scheme that will allow us to call landline numbers through our gateway.

In the **Number** field, create a regular expression that will be designed to dial a number with +, without +, with 8 or 7 at the beginning and the number of characters from 10 to 12:

```
^\+?(7|8)(\d{10,12})$
```

Now the scheme itself:

```
[
  {
    "ringback": {
      "call": {
        "name": "$${ru-ring}",
        "type": "tone"
      },
      "transfer": {
        "name": "$${ru-ring}",
        "type": "tone"
      }
    }
  },
  {
    "recordSession": {
      "action": "start",
      "type": "mp3",
      "stereo": "false"
    }
  },
  {
    "bridge": {
      "endpoints": [
        {
          "type": "sipGateway",
          "name": "74997045627",
          "dialString": "+7&reg0.$2"
        }
      ]
    }
  }
]
```

Highlights of the scheme:

- enable conversation recording.
- in dialString add + to the dialed number. \$ 2 is the second match in the regular expression - (\d {10,12}).